# Service Manual

# With Parts List For Automatic Linker

Model SC3

# CONTENTS

| [1] | NAMES OF COMPONENT PARTS  |
|-----|---|
| [2] | SC-3 DISASSEMBLY4   |
| [3] | SC-3 ASSEMBLY 7   |
| [4] | ADJUSTMENT OF EACH PARTS14  |
|     | 4-1 Dimensions of Main Machine14  |
|     | 4-2 Adjusting the Clearance between SC-3 and Main Machine Carriage Rail |
|     | 4-3 Connection Gear Adjustment16  |
|     | 4-4 Needle Fixing Cam Adjustment17                                      |
|     | 4-5 Transfer Needle Adjustment21  |
|     | 4-6 Correct Position of Fabric Holder23                                 |
| [5] | ADJUSTMENT AND MEASUREMENT OF EACH PARTS24                              |
|     | 5-1 Dimension between Sinker Post and SC Arm24                          |
|     | 5-2 Dimension between SC Arm and Fabric Holder25                        |
|     | 5-3 Dimension between Yarn Holder Base and Transfer Needle              |
|     | 5-4 Dimension between Fabric Holder and Transfer Needle26               |
| 161 | PARTS LIST27  |

# [1] NAMES OF COMPONENT PARTS

# 1-1 Surface:








Fig. 1




#### 1-3 Reverse Side:








3. Push the SC Plate up with your fingers as illustrated below and remove the SC Plate from the Cam Unit.








Fig. 9

2. While pulling at the Positioning Cam towards you, push the Cam Unit down gently. Then set the Feeding Stopper Spring so as it becomes engaged with a notch of the Cam Unit.






Fig. 10

3. Push the Cam Unit down by turning it to and fro, while pushing the Needle Cam A on the reverse side of the Carriage Unit towards the arrowed direction, until you can hear a click sound.




- 9 -

4. Push the Feeding Cam Base Axis strongly to the arrowed direction as illustrated below, and the Cam Unit will be interlocked with the SC Carriage completely.




Pig. 12

5. Secure the Cam Unit with one E Snap Ring 4.



6. Straighten out the nails of SC Plate.



7. Place the SC Plate on the Cam Unit and secure it with nails.





Fig. 15



#### [4] ADJUSTMENT OF EACH PARTS

#### 4-1 Dimensions of Main Machine:

- 1. The L Dimension (from the Rail to tips of Sinkers) is 121  $\pm$  0.25 m/m. (The range between the maximum and minimum measurement should be within 0.2 m/m.)
- 2. The dimension between the back surface of the Rail and the Needle Bed Rack is  $19.0 \pm 0.2 \text{ m/m}$ . (The difference between the maximum and minimum measurement should be within 0.2 m/m.)






Fig. 18

3. Sinker Post: 2.9 ± 0.4 m/m.



4. No extreme bend and/or breakage of Latch Needles.



Set the Linker on main machine and check the play between the Carriage Guide and Main Machine Carriage Rail.

- If the clearance is too large, it gives too much play to the Linker engaged with the Rail and causes the stitches to drop.
- o If the clearance is too small, the Linker becomes heavy to operate and the Connection Gear will run idle during operation.

# Correcting Method:

Loosen one each of # Binding Head Screws 3x6 and 3x16 and adjust the position of the Carriage Guide by moving it back and forth.





Fig. 21

#### 4-3 Connection Gear Adjustment:

If the Connection Gear does not engage with the needle bed rack correctly, it will cause drop stitches. Please check the balance with your eyes.

#### Correcting Method:

Loosen two # Binding Head Screws 3x4 which secure the Spring Holder and adjust the position of the Connection Gear by moving the Spring Holder back and forth as illustrated below.




- Move the Spring Holder forward The Connection Gear turns to left.
- . Move the Spring Holder backward The Connection Gear turns to right.

#### 4-4 Needle Fixing Cam Adjustment:

- 4-4-1 The vertical measurement between Needle Fixing Cam and front edge of main machine needle bed.
  - The Fixing Rack will engage with sinker post and at the same time the Needle Fixing Cam will be coming down when turn the Cam Unit so as the Crank Knob Arbour alignes to the centre of Connection Gear.

At this time, the measurement between the tip of Needle Fixing Cam and front edge of main machine bed must be 0.3  $\pm$  0.2 m/m.



#### 2. In case of too much space:

The yarn roop in the main machine needle can not be transferred to the Transfer Needle.

#### 3. In case of no space:

The tip of Needle Fixing Cam touches the needle bed and the Linker becomes too heavy to operate and this sometimes makes casting-off/joining impossible.

4. Take measure of clearance between the Needle Fixing Cam and front edge of main machine bed by using a Thickness Gauge.

Standard:  $0.3 \pm 0.2 \text{ m/m}$ .





Fig. 24

#### 5. Correcting Method:

Loosen two  $\theta$  Binding Head Screws (3x6) which secure the Positioning Cam and move it back and forth while pulling the Positioning Cam Base towards you.


- \* Move the Positioning Cam backward reduce the space.
- $\star$  Move the Positioning Cam forward increase the space.



4-4-2 The horizontal measurement between Needle Fixing Cam and Sinker Post.

The Needle Fixing Cam brings the main machine needle towards right when transfer the yarn roop to the Transfer Needle from main machine needle.

In order to make sure the transfer of roops, both of the vertical and horizontal adjustment should correctly be done.



#### Correcting Method:


Loosen one \$ Binding Head Screw (3x5) and adjust the clearance which should be within a range of 2.6 - 3.0 m/m. by moving the Needle Fixing Cam right and left.

#### 4-5 Transfer Needle Adjustment:

#### 4-5-1 Vertical Adjustment:

The Transfer Needle should be lower approx. 0.9  $\mbox{m/m}$ . than main machine needle.

Take measure of clearance between the tip of Transfer Needle hook and upper surface of SC Carriage by using a vernier calipers as illustrated below. (Standard  $17.1\pm0.2$ )




#### Correcting Method:

Loosen two & Round Head Tapping Screws (2, 2,3x6) and adjust the height of Transfer Needle.

#### 4-5-2 Horizontal Adjustment:

While the yarn roop is transferred, the clearance between needle hooks of main machine and Linker should have a range of  $0-0.4\ \text{m/m}$ . If the clearance is out of this range, it will cause the stitches to drop.



before transfer roops

while transferring roops

#### Correcting Method:

Loosen two 0 Round Head Tapping Screws (2, 2.3x5) which secure the Transfer Needle Unit and adjust the clearance by moving the Unit right and left.





Fig. 29

# 4-6 Correct Position of Fabric Holder:

| Cl | earance | of each part:-                       | m/  | /m    |
|----|---------|--------------------------------------|-----|-------|
| 1. | Sinker  | Post and SC Arm                      | 0 - | 0.3   |
| 2. | SC Arm  | and Fabric Holder                    | 0.8 | ± 0.1 |
| 3. | SC Arm  | and Fabric Holder                    | 1.4 | ± 0.2 |
| 4. | Top of  | Yarn Holder Bar and Transfer Needle: | 2.9 | - 3.3 |
| 5. | Fabric  | Holder and Transfer Needle           | 0.2 | ± 0.2 |




#### [5] ADJUSTMENT AND MEASUREMENT OF EACH PARTS

The following adjustments should be required for use of the Linker in good condition.

#### 5-1 Dimension between Sinker Post and SC Arm:


Loosen two  $\mbox{\ensuremath{\mathfrak{e}}}$  Binding Head Screws (3x5) which secure the Yarn Holder Base Unit and adjust the clearance between the Sinker Post and SC Arm by moving the Unit so that the clearance will fall within a range of 0.3 m/m.




(about 0.3 m/m.)

#### 5-2 Dimension between SC Arm and Fabric Holder:

a. Loosen one # Binding Head Screw (3x5) and adjust the clearance between the SC Arm and Fabric Holder by moving the Fabric Holder back and forth.




b. Turn the SC Carriage over and loosen two # Binding Head Tapping Screws (2, 2.6x6). Move the SC Arm right and left so that the clearance between the SC Arm and Fabric Holder will be within 1.2 - 1.6 m/m.



#### 5-3 Dimension between Yarn Holder Base and Transfer Needle:


Loosen two # Binding Head Screws (3x5) which secure the Yarn Holder Base Unit and adjust the clearance between the Yarn Holder Base and Transfer Needle.




#### 5-4 Dimension between Fabric Holder and Transfer Needle:


Loosen one # Binding Head Screw (3x5) which secure the Fabric Holder and Holder and adjust the clearance between the Fabric Holder and Transfer Needle by moving the Fabric Holder.

Check the clearance with a needle hook which is 0.7 m/m. thick.





| Ref.  | Parts No. | Description                     | Qty/set    | Common with SC-1 |
|-------|-----------|---------------------------------|------------|------------------|
| 1     | 04984803  | SC Carriage Unit                | 1          | 0                |
| 2     | 04874806  | Feeding Cam Base Unit           | 1          | 0                |
| .3    | 04804803  | Connection Gear Screw B         | 1          | 0                |
| 4     | 04794806  | Connection Gear                 | 1          | 0                |
| 5     | 04714804  | Connection Gear Screw A         | 1          | 0                |
| 6     | 04784807  | Spring Holder                   | 1          | 0                |
| 7     | 04774808  | Gear Spring                     | 1          | 0                |
| 8     | 03222007  | Collar 5x5                      | 1          | 0                |
| 9     | 04754800  | Feeding Spring A                | 1          | 0                |
| 10    | 04744801  | Feeding Spring B                | 1          | 0                |
| 11    | 04734802  | Feeding Spring C                | 2          | 0                |
| 12    | 04724803  | Feeding Cam Base Screw          | 1          | 0                |
| 13    | 04424800  | Slide Lever                     | 1          | 0                |
| 3. 43 | 04414801  | Slide Lever Holder              | Z          | 0                |
| 15    | 03954807  | Slide Lever Spring              | 1          | 0                |
| 16    | 04134805  | Slide Button (R)                | 1          | 0                |
| 17    | 04124822  | Slide Button (L)                | 1          | 0                |
| 18    | 04694808  | Yarn Holder Lever Unit          | 1          | O                |
| 19    | 04614806  | Yarn Holder Lever Spring A      | 1          | 0                |
| 20    | 04604807  | Yarn Holder Lever Spring B      | 1.         | 0                |
| 21    | 04584801  | Cam BC                          | 1          | 0                |
| 22    | 04574802  | Cam DE                          | 1          | 0                |
| 23    | 04564803  | Can F                           | 1          | 0                |
| 24    | 04554804  | Handle Base Unit                | 1          | 0                |
| 25    | 04484804  | Needle Cam Spring               | 1          | O                |
| 26    | 04394805  | Positioning Cam                 | 1.         | O                |
| 27    | 04384806  | Fixing Rack                     | 1.         | 0                |
| 28    | 03934809  | Positioning Cam Spring          | 1          | O                |
| 29    | 04304804  | Transfer Base Spring            | 1          | 0                |
| 30    | 03924800  | Carriage Auxiliary Plate        | 1          | 0                |
| 31    | 04114807  | Feeding Stopper Spring          | 1.         | 0                |
| 32    | 14034847  | Fabric Holder Base              | 1          | C                |
| 3.3   | 04024808  | Fabric Holder                   | 1          | 0                |
| 34    | 04104840  | Crank Knob                      | l          |                  |
| 35    | 04084851  | SC Plate                        | I.         |                  |
| 36    |           | Model Number Seal               | 1          |                  |
| 37    | 04014825  | SC Cover                        | 1          |                  |
| 38    | 04782561  | ⊕ Binding Head Screw 3x4        | Ž.         |                  |
| 39    | 05212006  | ⊕ Binding Head Screw 3x5        |            |                  |
| 40    | 01.332006 | ⊕ Binding Head Screw 3x6        | 4          |                  |
| 41    | 04741005  | ⊕ Binding Head Screw 3x14       | 1          |                  |
| 42    | 03804804  | Binding Head Screw 3x16         | 2          |                  |
| 43    | 02231207  | 🕀 Pan Head Tapping Screw 2, 2x6 | .2.        |                  |
| 44    | 02900611  | Binding Head Tapping Screw 2,   |            |                  |
|       |           | 3x10                            | 2          |                  |
| 45    | 08662116  | E Snap Ring 3                   | 2          |                  |
| 46    | 08672115  | E Snap Ring 4                   | green, and |                  |
| 47    | 06341002  |                                 | 2          |                  |
| 48    | 05922158  | Plain Washer 4.3x8x0.3          | 100        |                  |



| Ref. | Parts No. | Description                              | Qty/set | Common<br>with SC-1 |
|------|-----------|--|---------|---------------------|
| 1    | 04924809  | Rail Guide                               | 1       | 0                   |
| 2    | 04894804  | Carriage Guide                           | 1       | 0                   |
| 3    | 04524807  | Cam A                                    | 1       | 0                   |
| 4    | 04514808  | Needle Cam A                             | 1       | 0                   |
| 5    | 04504809  | Needle Cam B                             | 1       | 0                   |
| 6    | 04494803  | Needle Cam Collar                        | 1       | 0                   |
| 7    | 04094801  | Slider                                   | 1       | 0                   |
| 8    | 04474805  | Needle Fixing Cam Unit                   | 1       | 0                   |
| 9    | 04364808  | Transfer Base                            | 1       | 0                   |
| 10   | 04354809  | Transfer Needle Unit                     | 1       | 0                   |
| 11   | 04324802  | Transfer Base Holder A                   | ì       | 0                   |
| 12   | 04314803  | Transfer Base Holder B                   | 1       | 0                   |
| 13   | 04294807  | Yarn Holder Base Unit                    | 1       | 0                   |
| 14   | 04174801  | Gear A                                   | 1       | 0                   |
| 15   | 04154803  | Yarn Holder Spring                       | 1       | 0                   |
| 16   | 04144804  | Stopper Spring                           | 1       | 0                   |
| 17   | 04054805  | SC Arm                                   | 1       | 0                   |
| 18   | 04782561  | ⊕ Binding Head Screw 3x4                 | 3       | 0.7000              |
| 19   | 05212006  | ⊕ Binding Head Screw 3x5                 | 3       |                     |
| 20   | 01332006  | ⊕ Binding Head Screw 3x6                 | 2       |                     |
| 21   | 05220611  | ⊕ Binding Head Screw 3x8                 | 1       |                     |
| 22   | 03083201  | ⊕ Binding Head Screw 3x10                | 1       |                     |
| 23   | 03804804  | ⊕ Binding Head Screw 3x16                | 1       |                     |
| 24   | 06096002  | ⊕ Round Head Tapping Screw 2,<br>2.3X6   | 2       |                     |
| 25   | 05861000  | ⊕ Pan Head Tapping Screw 2,<br>2.6x10    | 2       |                     |
| 26   | 04206900  | ⊕ Binding Head Tapping Screw 2,<br>2.6x8 | 3       |                     |
| 27   | 08662116  | E Snap Ring 3                            | 2       |                     |
| 0    | 04004800  | Stylofoam Packing A                      | 1       |                     |
| 0    | 03994803  | Stylofoam Packing B                      | 1       |                     |
| 0    | 03984812  | Cardboard Wrapping                       | 1       |                     |
| 0    | 03974813  | Instruction Book                         | 1       |                     |
| 28   | 01040419  | ⊕ Binding Tapping Screw 2, 3x8           | 1       |                     |
| 29   | 06234009  | Plain Washer 3x8x1                       | î       |                     |
| 30   | 06342000  | Plain Washer 3x8x0.5                     | ~       |                     |
|      |           | (for Adjustment)                         | 2       |                     |
|      | 06341002  | Plain Washer 3x8x0.8                     | 2       |                     |
|      |           | (for Adjustment)                         | ~       |                     |
| 32   | 05014808  | Presser                                  | 1       | 0                   |